

HMPS1U



1-Port USB 2.0 Print Server for Multifunction Printers

HMPS1U

PACKAGE CONTENTS:

- ◆ One HMPS1U Print Server for Multifunction Printers
- ◆ Quick Installation Guide
- ◆ Multifunction Print Server Control Center Software CD with Manual
- ◆ Power Adaptor

1-Port USB 2.0 Print Server for Multifunction Printers

The Hawking HMPS1U Print Server for Multifunction Printers lets you connect and share your multifunction printer, scanner or USB storage device (USB thumb drive, hard drive etc...) with the computers in your home or office area network. Simply attach your multifunction printer or USB storage device to the Print Server, run the Utility Software and begin sharing your printer or storage device. The HMPS1U is also capable of sharing your USB storage device and USB printer over the internet for remote access and remote printing (FTP server, IPP printing). With the HMPS1U, your printer becomes a fully functional network print station.

Features

- ◆ Easily Connects Your Multifunction "All-In-One" Printer to a Network
- ◆ Print From Any Computer Over The Internet/Intranet
- ◆ 4 LED Indicators: POWER, LINK, ACTIVE and USB
- ◆ High Speed 2.0 Connection for Most USB Devices
- ◆ No Need for a Dedicated Print Server Computer
- ◆ Setup is Quick and Simple

System Requirements:

- ◆ Windows 2000/XP/2003 Server/ Vista (32-Bit)
- ◆ Multifunction Printer or USB Storage Device
- ◆ One available CD/DVD drive

HMPS1U

1-Port USB 2.0 Print Server for Multifunction Printers

SPECIFICATIONS:

Network Specifications:

- ◆ IEEE 802.3 10Base-T
- ◆ IEEE 802.3u 100Base-TX

Printer Interface

- ◆ USB 2.0, 1.1 Compliant USB Type A Port

LAN Port

- ◆ 10/100Mbps Auto-Negotiation UTP/STP RJ-45 Port

CPU/SDRAM/Flash ROM

- ◆ R3210-G, 150MHz x86 RISC,(RDC)/ 8MByte 64Mbits SDRAM/2 MByte 16bits Flash

Printer Interface

- ◆ USB 2.0, 1.1 Compliant USB Type A Port

Electrical Properties

- ◆ DC in: 12V/1A
- ◆ Power Consumption: Max 2.5W
- ◆ Power Support for USB Port: 5V/1A

OS Support

- ◆ Windows 2000/XP/2003/Vista

TCP/IP Protocol Supported

- ◆ DHCP, IPP, Raw TCP, LPR, SMB, SNMP, UPnP, FTP

LED

- ◆ Power, Link, Active, USB

Temperature

- ◆ Operating: 0°~50°C (32°~122°F)
- ◆ Storage: -25°~55°C (-13°~131°F)

Dimensions/Weight

- ◆ 80(L) * 60(W) * 25(H)mm/55g

Certification

- ◆ CE, FCC, RoHS Compliant

Warranty

- ◆ 2 year

RELATED PRODUCTS

HPS1P	10/100M 1 Parallel Port Print Server
HPS1U	1-Port USB High-Performance Internet Print Server
HWPS1UG	Wireless-G 1-Port USB Print Server
HWPS12UG	Wireless-G Multiple Port Print Server

HAWKING TECHNOLOGIES, INC

USA: Irvine, California

Sales: 888.662.8828 or 949.790.0800
Email: sales@hawkingeurope.com

Fax: 949.790.0880

Email: customersupport@hawkingtech.com

EUROPE: Rotterdam, The Netherlands

Sales: 31-10-245-1600
Email: sales@hawkingeurope.com

Fax: 31-(0)10-245 1616

Email: customersupport@hawkingeurope.com

READY, NETWORK & GO!

It's easy to install, it's easy to use! Everyone can do it.

Step 1 - Install your Multifunction Print Server (MFPS)

Plug in ethernet cord from Router, USB cord from printer, and power adapter.

Step 2 - Insert the Setup CD

Set up the MFPS via the Quick Setup Wizard

Step 3 - Access your MFPS

Launch your newly installed MFPS Control Center and access your MFP over the internet and your Local Area Network!

