



- **H-U2PS2**  
**USB 1.1 compliant**  
**Easy Installation**  
**Two Year Warranty**

**PACKAGE CONTENTS:**

- ◆ One USB to PS/2 Adapter



**Get Connected with Hawking**

The Hawking's H-U2PS2 USB to PS/2 Adapter is easy to install and use. It supports two PS/2 Devices (Keyboard and Mouse) and Converts them to a USB Interface. It also converts the PC PS/2 port of KVM switch to a USB port.

**System Requirements:**

- ◆ One Standard USB port
- ◆ Windows 98/2000/ME/XP; Netware 4.11, 5.0, HP Unix, Linux; or Mac OS 8.6 or higher; Sun Microsystems

**Specifications**

Function		Specification
Connector	USB	Type A Plug
Connector	PS/2	1 Keyboard(Purple color), 1 Mouse(Green Color)
Y Cable Length		USB End 10 cm (3.9 in.),PS/2 End 10 cm(3.9 in.)
Platforms		PC Windows 98/SE/ME; Windows 2000; Windows NT Netware 4.11, 5.0, HP Unix, Linux, Apple computer G3/G4 MAC O.S. 8.6 or greater, Sun Microsystems with USB interface
Transfer Rate		1.5Mbps
USB Specs.		1.0 and 1.1 Compatible
Power Mode		Bus Power (Via the USB cable)
Operating Temperature		5 ~ 40°C
Storage Temperature		-20 ~ 60°C
Humidity		0 ~ 80% RH, Non-condensing
Enclosure		Plastic
Weight		52 grams
Dimensions (length)		35.3 cm

- ◆ USB-PS2 For Sun Microsystems platforms, refer to table below

**PS/2 Keyboard**

Sun Microsystems Keyboard	Windows PS2 Keyboard
Stop	L_Win & L_Alt
Props	L_Win & L_Ctrl
Compose	L_Win & L_Shift
Front	L_Win & F1
Open	L_Win & F2
Find	L_Win & F3
Again	L_Win & F4
Undo	L_Win & F5
Copy	L_Win & F6
Paste	L_Win & F7
Cut	L_Win & F8
Help	L_Win & F11
Power	L_Win & F12
Mult 	L_Win & "1"
V_DN 	L_Win & "2"
V_UP 	L_Win & "3"

**HAWKING TECHNOLOGIES, INC**

USA: 6A Faraday, Irvine, CA 92618

Europe: Rotterdam, The Netherlands

**Sales:** 888.662.8828, 949.580.0888

**Fax:** 949.580.0880

**Email:** sales@hawkingtech.com

**Email:** techsupport@hawkingtech.com

**ORDERING INFORMATION:**

**H-U2PS2** PS2 to USB Adapter

**H-U225HD** 2.5" HD to USB Adapter

**H-UC232S** Serial Port to USB Adapter